EINDHOVEN UNIVERSITY OF TECHNOLOGY

Department of Mathematics

PROBABILITY THEORY, STATISTICS AND OPERATIONS RESEARCH GROUP

Memorandum COSOR 76-17

A simple proof of Heymann's lemma

by

M.L.J. Hautus

Eindhoven, November 1976

The Netherlands

A SIMPLE PROOF OF HEYMANN'S LEMMA

of

M.L.J. Hautus*

Abstract. Heymann's lemma is proved by a simple induction argument .

The problem of pole assignment by state feedback in the system

$$x_{k+1} = Ax_k + Bu_k ; \quad (k = 0, 1, \dots)$$

where A is an $n \times n$ -matrix and B an $n \times m$ -matrix, has been considered by many authors. The case $m = 1$ has been dealt with by Rissanen [3] in 1960. In 1964 Popov [2] showed the pole assignability for complex systems (more generally systems over an algebraically closed field). In 1967 Wonham gave a proof valid for real systems (or more generally for systems over an infinite field). Finally, in 1968, Heymann [1] gave a proof which is valid for systems over an arbitrary field. Heymann's proof depends on the following result.

LEMMA 1. *If (A, b) is controllable and $b = Bv \neq 0$, then there exists F such that $(A + BF, b)$ is controllable.*

By means of this result the multivariable problem can be reduced to the single variable problem.

It is the aim of this correspondence to give a simple proof of this lemma. The result follows immediately from

LEMMA 2. *If (A, B) is controllable and $b = Bv \neq 0$, then there exists $u_1, \dots, u_{n-1}$ such that the sequence defined by*

$$(1) \quad x_1 := b \quad , \quad x_{k+1} := Ax_k + Bu_k \quad ,$$

for $k = 1, \dots, n - 1$ is independent.

* Dept. of Math., Eindhoven University of Technology

Indeed, if Lemma 2 is shown we can choose u_n arbitrary and define F by $Fx_k = u_k$. Then it is easily seen that $(A + BF)^k b = x_k$, so that $(A + BF, b)$ is controllable.

PROOF OF LEMMA 2. We proceed stepwise. $x_1 \neq 0$ and hence independent. Suppose that $x_1, \dots, x_k$ have been constructed according to (1) and are independent. Denote by $\mathcal{L}$ the linear space generated by $x_1, \dots, x_k$. We have to choose u_k such that $x_{k+1} = Ax_k + Bu_k \notin \mathcal{L}$. If this is not possible, then

$$(2) \quad Ax_k + Bu \in \mathcal{L}$$

for all u . Choosing in particular $u = 0$ we find

$$(3) \quad Ax_k \in \mathcal{L}$$

and consequently, by the linearity of $\mathcal{L}$, $Bu \in \mathcal{L}$ for all u . That is, $\text{im} B \subseteq \mathcal{L}$. Also, for $i < k$ we have

$$Ax_i = x_{i+1} - Bu_i \in \mathcal{L}$$

Hence $Ax_i \in \mathcal{L}$ for $i = 1, \dots, k$, and, consequently, $\mathcal{L}$ is A -invariant. From the controllability of (A, B) it follows that $\mathcal{L}$ must be the whole state space, which implies that $k = n$. □

REMARK. In [1] and in [5, Lemma 2.2] proofs of Lemma 1 were given by constructing a particular sequence u_k satisfying the condition of Lemma 2. These constructions may suggest that such a special u_k is essential for the calculation of F , which is not the case as follows from the proof of Lemma 2. It also follows that the u_k 's can be constructed recursively in the following sense: Once $u_1, \dots, u_{\ell-1}$ have been chosen so as to render $x_1, \dots, x_{\ell}$ independent, one can always continue the construction of the remaining u_k 's. This may be useful when it comes to an actual numerical computation of F .

REFERENCES

- [1] M. Heymann, *Comments on "Pole Assignment in Multi-Input Controllable Linear Systems"*. IEEE Trans. Automatic Control, AC-13 (1968), pp. 748-749.
- [2] V.M. Popov, *Hyperstability of control systems with several control functions*, Rev. Roumaine des Sciences Techniques, série Electr. et En., 1964, 9.
- [3] J. Rissanen, *Control system synthesis by analogue computer based on the "generalized linear feedback" concept*, International Seminar on "Analog computation to the study of chemical processes", Brussels, 1960.
- [4] W.M. Wonham, *"On pole assignment in multi-input controllable linear systems"*, IEEE Trans. Aut. Contr. AC-12 (1967), p. 660-665.
- [5] W.M. Wonham, *"Linear multivariable control; A geometric approach"*, Lecture Notes in economics and mathematical systems No.101, Springer-Verlag, Berlin, 1974.